## ASUS TUF GAMING A620M-PLUS AMD A620 Socket AM5 micro ATX

Merk: ASUS Artikelcode: 90MB1EZ0-M0EAY0

**Productnaam:** TUF GAMING A620M-PLUS

ASUS TUF GAMING A620M-PLUS. Processorfabrikant: AMD, Processor socket: Socket AM5, Compatibele processors: AMD Ryzen 7000 Series. Ondersteunde geheugen types: DDR5-SDRAM, Maximum intern geheugen: 128 GB, Geheugen slots type: DIMM. Ondersteunde opslagstationinterfaces: M.2, SATA III, Ondersteunde types opslag-drives: HDD & SSD, Soorten RAID: 0, 1, 10. Ethernet interface type: 2.5 Gigabit Ethernet. Component voor: PC, Moederbord form factor: micro ATX, Moederbord chipset familie:





Processor		Rear panel I/O ports	
Processor manufacturer * Processor socket * Compatible processor series * Supported processor sockets	AMD Socket AM5 AMD Ryzen 7000 Series Socket AM5	USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity * Ethernet LAN (RJ-45) ports * PS/2 ports quantity	2 1 1
Memory Supported memory types * Number of memory slots * Memory slots type Memory channels ECC compatibility Supported memory clock speeds	DDR5-SDRAM 4 DIMM Dual-channel ECC & Non-ECC 4800,5000,5200,5400,5600,5800,6000,6200,6400 MHz	HDMI ports quantity * HDMI version DisplayPorts quantity DisplayPort version Headphone outputs Line-in Network	1 2.1 2 1.4 1
Supported memory clock speed (max)  Maximum internal memory *  Storage controllers	6400 MHz 128 GB	Ethernet LAN Ethernet interface type Wi-Fi *	✓ 2.5 Gigabit Ethernet ×
Supported storage drive types Supported storage drive interfi Number of HDDs supported Number of storage drives supp RAID support	aces * M.2, SATA III 4	Features  Motherboard chipset * Audio output channels * Component for * Motherboard form factor * Motherboard chipset family *	AMD A620 7.1 channels PC micro ATX AMD
Graphics Parallel processing technology support * Internal I/O	Not supported	Cooling type Power source type Windows operating systems supported	Passive ATX Windows 10, Windows 11
USB 2.0 connectors * USB 3.2 Gen 1 (3.1 Gen 1) connectors * Number of SATA III connectors	2 2 * 4	Expansion slots PCI Express x1 (Gen 3.x) slots PCI Express x16 (Gen 4.x) slots Number of M.2 (M) slots	2 1 2

Internal I/O		BIOS	
S/PDIF out connector Front panel audio connector	<b>/</b>	BIOS type * BIOS memory size	UEFI AMI 256 Mbit
ATX Power connector (24-pin)	<b>✓</b>	Packaging data	
CPU fan connector Number of chassis fan connectors EPS power connector (8-pin) Number of COM connectors	2 2 1	Package width Package depth Package height Package weight	275 mm 275 mm 67.5 mm 850 g
12V power connector	<b>✓</b>	Weight & dimensions	
RGB LED pin header	✓	Width	244 mm
Rear panel I/O ports		Depth	244 mm
USB 2.0 ports quantity *	4	Packaging content	
		Cables included	SATA
		User guide	✓
		Other features	
		Back-to-BIOS button	✓



4711387164303

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.